

# POWERPLAY PRO-8 HA8000



## Technical Specifications

VERSION 1.2 February 2003

ENGLISH

[www.behringer.com](http://www.behringer.com)



## POWERPLAY PRO-8 HA8000

# POWERPLAY PRO-8

### 8-CHANNEL HIGH-POWER HEADPHONES DISTRIBUTION AMPLIFIER



- ▲ Professional multi-purpose headphones amplifier system for stage and studio applications
- ▲ Eight totally independent stereo high-power amplifier sections in one rack space
- ▲ Two stereo Main inputs for two independent mixes, accessible from all eight channels
- ▲ Eight independent Direct inputs provide up to eight individual stereo mixes
- ▲ Highest sonic quality with virtually all types of headphones even at maximum volume
- ▲ Output level control and accurate 8-digit LED output meter per channel
- ▲ Mono/stereo switch per channel for more flexibility
- ▲ One front and one rear 1/4" TRS phones connector for each channel
- ▲ Direct input connector on each channel for easy connection of any sound source
- ▲ Paralleled outputs allow cascading of several headphones amplifiers
- ▲ Toroidal transformer for noiseless operation and low magnetic interference
- ▲ High-quality components and exceptionally rugged construction ensure long life
- ▲ Conceived and designed by BEHRINGER Germany

## SPECIFICATIONS

### AUDIO INPUTS

MAIN IN	HF-filtered, servo-balanced 1/4" TRS connectors
Input impedance	40 k $\Omega$ balanced, 20 k $\Omega$ unbalanced
Max. input level	+16 dBu balanced and unbalanced
CMRR	typically 40 dB, >55 dB @ 1 kHz
DIRECT IN	1/4" TRS connector (stereo)
Input impedance	15 k $\Omega$

### AUDIO OUTPUTS

PHONES OUTPUTS	1/4" TRS connector (stereo)
----------------	-----------------------------

### POWER AMPLIFIER

Max. output power	+24 dBm (load impedance 100 $\Omega$ )
Min. output load impedance	100 $\Omega$

### SYSTEM SPECIFICATIONS

Frequency response	10 Hz to 150 kHz, +/-3 dB
Noise	22 Hz to 22 kHz >90 dB @ 0 dBu
Dynamic range	22 Hz to 22 kHz: 110 dB
Distortion (THD)	0.006 % typ. @ +4 dBu, 1 kHz, Gain 1

### FUNCTION CONTROLS

Input Level	variable
Output Level per channel	variable

### FUNCTION SWITCHES

Main In 1/Main In 2	switches between Main Input 1 and Main Input 2
Mono	switches this section to mono

### DISPLAYS

Input level	4-digit LED-display: -30/-12/0 dB/CLIP
Output level	8-digit LED-display: -30/-24/-18/-12/-6/-3/0 dB/CLIP

### POWER SUPPLY

Mains voltage	
USA/Canada	120 V~, 60 Hz
Europe/U.K./Australia	230 V~, 50 Hz
Japan	100 V~, 50 - 60 Hz
General export model	120/230 V~, 50 - 60 Hz
Power consumption	30 W
Fuses	100 - 120 V ~: T 630 mA H 200 - 240 V ~: T 315 mA H
Mains connection	standard IEC receptacle

### DIMENSIONS AND WEIGHT

Dimensions (H x W x D)	approx. 1 3/4" (44.5 mm) * 19" (482.6 mm) * 8 1/2" (217 mm)
Weight	approx. 5.19 lbs. (2.35 kg)

BEHRINGER is constantly striving to maintain the highest professional standards. As a result of these efforts, modifications may be made from time to time to existing products without prior notice. Specifications and appearance may differ from those listed or illustrated.

# POWERPLAY PRO-8 HA8000

---

---

The information contained in this publication is subject to change without notice. No part of this publication may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording of any kind, for any purpose, without the express written permission of BEHRINGER Spezielle Studiotechnik GmbH.

BEHRINGER and POWERPLAY are registered trademarks. ALL RIGHTS RESERVED.

© 2003 BEHRINGER Spezielle Studiotechnik GmbH.

BEHRINGER Spezielle Studiotechnik GmbH, Hanns-Martin-Schleyer-Str. 36-38, 47877 Willich-Münchheide II, Germany

Tel. +49 (0) 21 54 / 92 06-0, Fax +49 (0) 21 54 / 92 06-30

---